

## Interior alarm via radio



- Indoor radio alarm of 95dB at 1 meter
- Remote programming
- Fire and burglary sounds
- Programmable 3/5/10 minutes
- Periodic supervision signals
- Tamper protection
- EN50131 Grade 2 Certificate



| Reference / Model   | VESTA-373 / SR-35-F1 |
|---|----------------------|
| Output level of 95dB at 1 meter                                   |                      |
| Possibility of remote programming                                 |                      |
| Differentiated sounds for intrusion and fire                      |                      |
| Lightweight and flexible to install                               |                      |
| Programmable alarm siren with 3/5/10 minute durations             |                      |
| Audible notifications of arming, disarming and low battery status |                      |
| Periodic supervisory signals to verify system integrity           |                      |
| Tamper protection prevents unauthorized removal and sabotage      |                      |
| Low battery detection   |                      |
| Compatible with VESTA F1 Alarm Panels                             |                      |
| RF frequency: 868MHz  |                      |
| Power supply: 2 AA lithium L91 batteries                          |                      |
| Battery life up to 3 years  |                      |



## Interior alarm via radio

| Reference / Model                            | VESTA-373 / SR-35-F1 |
|--|----------------------|
| Operating temperature -10°C ~ +45°C          |                      |
| Relative humidity up to 85% (non-condensing) |                      |
| Dimensions: 105 (W) x 105 (H) x 31 mm        |                      |
| CE compliant                                 |                      |
| EN50131 Grade 2 Certificate                  |                      |